

video borescope inspection

General information about pipe and duct video borescope inspection system AD-P2016REKLC

- ✓ Video Inspection Camera for Pipe, Duct, Sewer, Drain, Plumbing FLX 1089REKLC
- √ For dia 25mm to 150mm(1"- 6") pipelines
- √ ø23mm stainless steel color camera head
- √ 12pcs adjustable LED
- ✓ Reel with 30m of 5.2mm dia Push Rod
- √ 7" LCD screen with sunshade, DVR supports voice recording, video
- √ recording, taking picture by any SD card (8GB SD card Included)
- ✓ Includes 3 skids: 40mm; 80mm; 120mm









Technical specification of the device:

29mm camera head(removable):

- Total Pixels: PAL:710X576; NTSC:720X480
- Camera size:Ø29mm
- Camera built-in 512Hz sonde(transmitter)
- View angle:120°
- Sensor size: 1/4 CMOS 700TVL
- Camera shell material:stainless steel
- Camera glass material:sapphire glass

LED Lights (adjustable):

- LED Lights:15LEDS
- Brightness of the LEDS:Controllable


8inch screen:

- Size of the screen:8" LCD Monitor
- 4:3 model
- Total Pixels:800X600
- Monitor power supply:DC 12V
- OSD language:English
- Remote controller
- Sunshade include

Control box:

- Video format:AVI
- Picture format:MPEG2
- Memory card:8G(Maximum 64G)
- Audio, video, photo recording & playback function
- Digital clock and calendar
- Battery level indicator lights
- LED brightness adjustable
- On / off microphone
- Up, down, left, right adjustable
- Video output to another screen







Cable reel:

- Length: 20m standard cable; 20-40m(optional)
- Diameter:5mm
- Distance counter
- Meter/foot
- Reel size: L51xW25xH64cm

Keyboard:

- Removable USB keyboard
- lead wire
- USB port keyboard connect to DVR controller for text input
- Language:English;

Centering skid:

 Dia 50mm/165mm:make the camera in the center of the pipe, and protect the camera head

Power supply:

- Li-ion Battery:DC12V 6600mah
- Working time: In operation(LED on): 6 hours

Case:

- Material:engineering plastics
- Color optional:orange/black
- The total weight includes all components
- 12KG-52X45X21cm



